

# Product Compatibility

## Compatible products

Here's a brief list to help you identify compatible products.

DirectLogic	Compatible
<b>DL05</b>	None
<b>DL06</b>	None
<b>DL105</b>	None
<b>DL205</b>	None
<b>DL305</b>	GE Series 1 TI 305 Simatic TI 305
<b>DL405</b>	TI 405 Simatic TI405

## Compatible communication drivers

DirectLogic	Compatible
<b>DirectNet</b>	CCM (GE) Hostlink (TI/Siemens)

A driver created for a compatible PLC will probably work with our PLCs. However, some of our newer CPUs have more memory than similar products offered by previous vendors. If using one of their drivers, make sure you ask if their driver performs memory range checking. If it does, then you may not be able to access all of the memory locations.

## Communication protocols

Some vendors may specify a communication protocol instead of a PLC family name. Use the chart shown on this page to help you identify the protocol and PLC port usage.

	CPU/ device	Port	Protocol
<b>DL05 DL06</b>	D0-05	Port 1	K-sequence, <b>DirectNET</b> and Modbus RTU slave
		Port 2	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
	D0-06	Port 1	K-sequence, <b>DirectNET</b> and Modbus RTU slave
		Port 2	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
	D0-DCM	Port 1	K-sequence, <b>DirectNET</b> and Modbus RTU slave
		Port 2	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
<b>DL105</b>	F1-130	Only one	K-sequence slave
<b>DL205</b>	D2-230	Only one	K-sequence slave
	D2-240	Top port	K-sequence slave
		Bottom port	K-sequence and <b>DirectNET</b> slaves
	D2-250-1	Top port	K-sequence, <b>DirectNET</b> and Modbus RTU slaves
		Bottom port	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
	D2-260	Top port	K-sequence, <b>DirectNET</b> and Modbus RTU slaves
		Bottom port	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
	D2-DCM (module used with D2-240/250-1/260)	Only one	K-sequence slave <b>DirectNET</b> master/slave Modbus RTU slave
<b>DL305</b>	D3-330	Requires DCU	<b>DirectNET</b> slave
	D3-330P	Requires DCU	<b>DirectNET</b> slave
	D3-340	Top port	<b>DirectNET</b> slave
		Bottom port	<b>DirectNET</b> master/slave Modbus RTU slave
	D3-350	Top port	K-sequence and <b>DirectNET</b> slave
		Bottom port	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
	D3-DCM (module used with D3-350 CPU)	Only one	K-sequence slave <b>DirectNET</b> master/slave Modbus RTU slave
<b>DL405</b>	D4-430	Top port (15-pin)	K-sequence slave
		Bottom port (25-pin)	K-sequence and <b>DirectNET</b> slave
	D4-440	Top port (15-pin)	K-sequence slave
		Bottom port (25-pin)	K-sequence and <b>DirectNET</b> slave
	D4-450	Phone jack	K-sequence and <b>DirectNET</b> slave
		Top port (15-pin)	K-sequence slave
		Bottom port (25-pin)	K-sequence slave, <b>DirectNET</b> and Modbus RTU master/slave
	D4-DCM (module)	Only one	K-sequence slave <b>DirectNET</b> master/slave Modbus RTU slave